CAMERA READY COPY TRANSMITTAL SHEET

6317592

TODAY'S DATE 2/5/01

WEEK ~~ISSUE~~ DATE 1/15/01

PATENT #	TOTAL PAGES
5355418	12
(09/455,409)	

```
#define ATT_EMAIL_FILE          "TFMOBOX.TMP"
#define DELIMITER               "End of Telefind Network Message\n"
```

```
#include <string.h>
#include <time.h>
#include <stdio.h>
#include <dos.h>
#include "safari.h"

void main(void)
{
        FILE *infile,*outfile;
        char buffer[81],chr,timestr[6],datestr[9];
        char msg_num[4];
        int msg_num_opt = 0;
        char *ptr;
        int x,day,month,line=1,attmail=0;
        time_t t;

        if ((infile = fopen(ATT_EMAIL_FILE,"rt")) == NULL)
        {
                printf("%s does not exist\n",ATT_EMAIL_FILE);
                exit(0);
        }
        if ((outfile = fopen("tfmobox.$$$","wt")) == NULL)
        {
                printf("Can't open TFMOBOX.$$$\n");
                exit(0);
        }

        for(;;)
        {
                /*      get characters from .tmp file   */
                x = 0;
                do
                {
                        chr = fgetc(infile);
                        if (feof(infile))
                        {
                                fclose(infile);
                                fclose(outfile);
                                exit(0);
                        }
                        buffer[x++] = chr;
                }
                /*          until end of line          */
                while (chr != '\n' && x != 80);

                buffer[x] = '\0';       /*     terminate it     */

                if (line == 1)
                {
                        ptr = strchr(buffer,')');
                        if (ptr-buffer == 2)    /*   was 3rd character  */
                        {
                                sscanf(buffer,"%[^)]",msg_num);
                                msg_num_opt = 1;
                                ptr++;
                        }
                        else
                                ptr = buffer;

                        if (*ptr == ':' && *(ptr+1) == '0')
                                attmail = 1;
                }

                if (attmail)
                {
                        switch(line)
```

```
        {
                case 1:
                        /*      datestr = mm/dd, timestr = hh:mm        */

                        sscanf(datestr,"%d/%d",&month,&day);            */
                        /*      get year from pc        */

                        t = time(NULL);
                        fprintf(outfile,"Date: %s",ctime(&t));
                        break;
                case 2:
                        fprintf(outfile,"From: %s",buffer);
                        break;
                case 3:
                        fprintf(outfile,"Subject: %s",buffer);
                        fprintf(outfile,"To: <Name here>\n");
                        if (msg_num_opt)
                                fprintf(outfile,"Message #%s\n",msg_num);
                        break;
                default:
                        fprintf(outfile,"%s",buffer);
                        break;
        }
    }
    else
    {
        if (line == 1)
        {
                t = time(NULL);
                fprintf(outfile,"Date: %s",ctime(&t));
                fprintf(outfile,"From: tfmobox\n");
                fprintf(outfile,"Subject: Telefind Network Message\n");
                fprintf(outfile,"To: <Name here>\n");
                if (msg_num_opt)
                {
                        fprintf(outfile,"Message #%s\n",msg_num);
                        fprintf(outfile,"%s",buffer+3);
                }
                else
                        fprintf(outfile,"%s",buffer);
        }
        else
                fprintf(outfile,"%s",buffer);
    }

    if (strcmp(buffer,DELIMITER) == 0)
    {
        msg_num_opt = line = attmail = 0;
    }

    line ++;
}
```

```
        Author:                 MICHAEL P. [redacted]NSCHKE, SR.
                                03/13/91

        Program:                SAFARI3.C
        Purpose:                TO EXTRACT MESSAGES FROM A TELEFIND PAGER
                                VIA IN RS-232 PORT ON A PC

        Compiler:               TURBO C++ 1.0
        Memory Model:           SMALL
*/

#include <dos.h>
#include <stdio.h>
#include <conio.h>
#include <string.h>
#include <stdlib.h>
#include "safari.h"

/*              CONSTANTS               */


#define DTR_HI                  0x01
#define DTR_LO                  0xfe
#define RTS_HI                  0x02
#define RTS_LO                  0xfd
#define DSR_HI                  0x20
#define RING_IN                 0x40
#define CD_HI                   0x80
#define FIVE_TICK               5
#define FIVE_SEC                96
#define TWELVE_SEC              220
#define LOG_FILE                "LOG"
#define INTRO_STRING            "Please standby, retrieving messages ..."

/*    FUNCTION PROTOTYPES       */

int beep(void);
void busyoff(void);
void busyon(void);
void dioff(void);
void dion(void);
int link(void);
void print_message(void);
int rxdata(void);
int strobe(void);
int strobe_data(void);
unsigned ticks(void);
int timeout(unsigned start, int delay);

/*   VARIABLE DECLARATIONS      */

char pager_buffer[511];
int com_base,control_reg,status_reg,log_flag;
FILE *log_file;

void main(int num_arg, char **args)
{
        unsigned start;
        int restart,x;

        com_base = 0x3f8;       /*    use com 1 unless command line denotes otherwise   */

        /*      get command line arguments      */
```

```
all command line arguments begin with a single '-' and
must be seperated by a single space between each other
and the program name

-1      Use COM port 1
-2      Use COM port 2
-F      Log all activity to a file named LOG            */

if (num_arg > 1)
{
        for (x=1; x<num_arg; x++)
        {
                if (strcmp(args[x],"-1") == 0)
                        com_base = 0x3f8;
                if (strcmp(args[x],"-2") == 0)
                        com_base = 0x2f8;
                if (strcmp(args[x],"-F") == 0)
                        log_flag = 1;
        }
}

if (log_flag)
        if ((log_file = fopen(LOG_FILE,"at")) == NULL)
                printf("Unable to open LOG\n");

control_reg = com_base + 4;
status_reg = com_base + 6;

clrscr();

if (link() == 0)        /*    is pager attached ?       */
        {
        printf("Please attach Message Receiver \n");
        exit(0);
        }

busyon();               /*  start busy at logic high    */

if (log_flag)
        fprintf(log_file,"Initiating process \n");
printf("%s\n",INTRO_STRING);
disON();        /* push display button  */
sleep(2);
do
{
        start = ticks();
        restart = 0;
        do
        {
                if (beep())
                {
                        print_message();
                        restart = 1;
                        start -= TWELVE_SEC;
                        break;
                }
        }
        /* hold display button for 12 seconds   */
        while(! timeout(start,TWELVE_SEC));
}
while(restart);

disoff();       /* release the display button   */
if (log_flag)
{
        fprintf(log_file,"Process Complete \n");
```

```
                fclose(log_file);
        }

}

/*              pager beep              */
int beep(void)
{

/*      accesses the RI line via the Status Register
        which is activated when the pager beeps         */

        unsigned start;

        start = ticks();
        while ( ! timeout(start,FIVE_TICK))
        {
                if ((inportb(status_reg) & RING_IN) == 0 )
                        return(1);
        }
        return(0);
}

/*      busyon & busyoff toggle the DTR line via the
        Control Register to strobe in data from the pager                       */

void busyoff(void)
{
        outportb(control_reg,inportb(control_reg) | DTR_HI);
}

void busyon(void)
{
        outportb(control_reg,inportb(control_reg) & DTR_LO);
}

/*      dison & disoff toggle the RTS line via the Control Register
        to simulate the pressing of the display button on the pager             */

void dison(void)
{
        outportb(control_reg,inportb(control_reg) | RTS_HI);
}

void disoff(void)
{
        outportb(control_reg,inportb(control_reg) & RTS_LO);
}

int link(void)
{

/*      accesses the CD line via the Status Register
        which is logic high when pager is connected     */

        if ((inportb(status_reg) & CD_HI) == 0)
                return(0);
        return(1);
}

void print_message(void)
{
        FILE *file;
        unsigned start;
        int x,y=0,z=0,chr,bit;
```

```
busyoff();      /*      ready to accept pager data      */

/*              read until end code received            */
while (chr != 3)
{
        chr = 0;
        start = ticks();

        /*      wait for start bit      */

        do
        {
                bit = strobe();
                if (bit == 0)
                        break;
        }
        while (!timeout(start,FIVE_SEC));

        if (bit)
        {
                if (log_flag)
                        fprintf(log_file,"Transmission Error, recheck connection\n");
                disoff();
                exit(0);
        }

        /*              strobe out 8 bit data           */

        for (x=1; x<9; x++)
        {
                chr <<= 1;
                chr += bit = strobe_data();
        }

        /*              clear out stop bits             */
        for (x=1;x<3;x++)
        {
                strobe_data();
        }

        /*   extract start and end codes from message

             pager signon       02, 18, 0D, 33
             pager signoff      03                      */

        if ((y > 3) && (chr != 3))
        {
                /* pager characters 96 and 97 are converted to
                   0xFA and 0xFB to display on pager            */

                if (chr == 0xfa)        /*    convert to CR     */
                        chr = '\n';
                if (chr == 0xfb)        /*    convert to TAB    */
                        chr = 0x09;

                pager_buffer[z] = chr;
                z ++;
        }
        y ++;
}

pager_buffer[z] = '\0';                 /*    null terminate    */

busyon();   /*        finished receiving data           */
```

```
        if (log_flag)
                fprintf(log_file,"%s\n",pager_buffer);

        if ((file = fopen(ATT_EMAIL_FILE, "at")) == NULL)
                fprintf(log_file,"Unable to open TFMOBOX.TMP\n");
        else
        {
                fprintf(file,"%s\n",pager_buffer);
                fprintf(file,"%s",DELIMITER);
                fclose(file);
        }

        start = ticks();
        while(!timeout(start,FIVE_SEC))
        {
        /*      wait for erase beep      */
                if (beep()) break;
        }
        sleep(1);       /*      wait one more second    */
}

int rxdata(void)
{

/*      accesses the DSR line via the Status Register
        which returns the bits value                    */

        if (inportb(status_reg) & DSR_HI)
                return(0);
        return(1);
}

int strobe(void)
{
        int bit;

        busyon();
        delay(1);
        busyoff();
        delay(4);
        bit = rxdata();
        return(bit);
}

int strobe_data(void)
{
        int bit;

        busyon();
        delay(2);
        bit = rxdata();
        busyoff();
        delay(1);
        return(bit);
}

unsigned ticks(void)
{
        /*      returns timer ticks (approx. 18.2/sec)
                using only lower registers              */

        union REGS in,out;

        in.x.ax = 0x0;
        int86(0x1a,&in,&out);
        return(out.x.dx);
```

```
timeout(unsigned start, int delay)

    /*      used for timing events of up to approx. 1 hour.
            used in conjunction w/ticks()                   */

    unsigned current;

    current = ticks();
    if (start <= current && (start + delay) < current)
            return(1);
    if (start > current && (start - 65535 + delay) < current)
            return(1);
    return(0);
```

```
        /* mark the end of the command line you built,so you can add ending
           delimiter */
        sys_command[i] = NULL;
        /* add the ending quote for the users message so shell wont
           interepert special characters */
        strcat(sys_command, "\'");
        /* execute command you built */
        system(sys_command);

        printf("sending message: %s\n", sys_command);

      }
      else {
        if(strlen(mesg) == 0 ) {
           return(0);
        }
        /* print error for invalid message length */
        printf("telemail error: invalid message length: %s\n", mesg);
        return(0);
      }

      return(i);
}

/*************************************************************************
*
*    function: getline(hold-buffer, input-file-pointer)
*    arguments: pointer to buffer where line read will be heald,
*               file pointer to input file
*    description: reads 1 line of text from the input line and stores the
*                 line read into the buffer passed.
*    returns: -1 if EOF or number of characters read in
*
*************************************************************************/
getline(buff, fp)
char *buff;
FILE *fp;
{
   int ch, cnt;

   /* keep on reading characetrs from file so long as end of file not
      reached or char is the end of line */
   for(cnt = 0; ((ch = fgetc(fp)) != EOF) && ch != '\n'; cnt++) {
       /* MOD BY OT 11/29/90 convert tab to space */
       /* convert tabs to single space */
       if(ch == 9) {
          ch = ' ';
       }
       /* MOD BY OT 11/29/90 dont allow control char */
       /* only load in ascii characters */
       if(isprint(ch) != 0) {
          buff[cnt] =  ch;
       }
       else {
             /* turn control characters to spaces */
             buff[cnt] = ' ';
       }
   }
   /* mark the end of the buffer you built */
   buff[cnt] = '\0';
```

```
/*************************************************************************
*
*    function: send_mesg(message-pointer)
*    arguments: pointer to text message(capcode,text) to be sent
*    description: takes passed message text makes sure the first 8 positions
*                 are numeric(capcode). it builds and executes the network
*                 send command(netsend.sh) to sedn the message passed.
*    returns: 0 if not sent otherwise the number of characters sent out
*
*************************************************************************/
int send_mesg(mesg)
char *mesg;
{
   char sys_command[700];
   int i;
   int ch;
   char *mesg_ptr;

   /* left justify the message passed to remove leading spaces */
   strljust(mesg, 512);
   /* trim off trailing blank spaces from the message */
   strtrim(mesg);

   /* make sure you have a capcode at least */
   if(strlen(mesg) > 8) {

      /* start to build the command to be executed to send message retreieved
         from the mail box */
      strcpy(sys_command, "netsend.sh ");

      /* loop while still more characters in the message */
      for(mesg_ptr = mesg, i = 11; *mesg_ptr != NULL; i++, mesg_ptr++) {

          /* make sure the first 8 positions of the message are numeric */
          if((i < 19) && (*mesg_ptr < '0' || *mesg_ptr > '9')) {
              printf("telemail error: invalid capcode: %s\n", mesg);
              return 0;
          }

          /* is the user didsnt seperate capcode & message then insert a
              space into the command */
          if(i == 19 && *mesg_ptr != ' ') {
             sys_command[19] = ' ';
             i = 20;
          }

          /* enclose the users message with ' so shell wont interpet
             special characters */
          if(i == 20) {
             sys_command[20] = '\'';
             i = 21;
          }

         /* put the character from the message onto to the
            command to be executed */
         sys_command[i] = *mesg_ptr;

      }
```

```
   /* since your just starting clear the message area */
   memset(mesg, NULL, MAXMSGLEN);

   /* keep on geting lines from the file until you reach end of file */
   while(getline(buff, fp) != -1) {

      /* every mail message start with the word "From " */
      if(strncmp(buff, "From ", 5) == 0) {
         /* set flag telling you are currently going thru mail header
            so you dont add it to the message */
         in_header = 1;
         /* call routine to the last message if any exists */
         send_mesg(mesg);
         continue;
      }

      /* a mail header end with the following string */
      if(strncmp(buff, "Content-Length:", 15) == 0) {
         /* turn off flag so you know you are no longer in mail
            message header */
         in_header = 0;
         /* clear the old message since this is a new one */
         memset(mesg, NULL, MAXMSGLEN);
         continue;
      }

      /* if the line you are now reading in not part of the mail header
         add it to the message */
      if(in_header == 0) {
         strljust(buff, 512);
         strtrim(buff);
         /* make sure you dont add more than the message length */
         if( (strlen(buff) + strlen(mesg)) < MAXMSGLEN) {
            strcat(mesg, " ");
            strcat(mesg, buff);
         }
      }

   } /* end of read line while */

   /* send the last message in the file */
   send_mesg(mesg);

}
```